St	Ba	Ex	Value	Function
				PAN Movement 8bit
			0-255	Pan Movement By 630/540
				Pan Fine 16bit
			0-255	Fine control of Pan movement
				TILT Movement 8bit
			0-255	Tilt Movement
				Tilt Fine 16bit
			0-255	Fine control of Tilt movement
				Speed pan/tilt movement
				max to min speed
				blackout by movement
				blackout by color/gobo
				Shutter, strobe
			0-31	Shutter closed
			32-63	No function (shutter open)
			64-95	Strobe effect slow to fast
			96-127	No function (shutter open)
			128-159	Pulse-effect in sequences

Focus

Continuous adjustment from far to near

Focus Fine

Continuous adjustment Fine

Color Wheel

0-15	Open / white	
16-31	Color 1	1
32-47	Color 2	2
48-63	Color 3	3
64-79		

90-109	Gobo 2 shake slow to fast	2
110-129	Gobo 3 shake slow to fast	3
130-149	Gobo 4 shake slow to fast	4
150-169	Gobo 5 shake slow to fast	5
170-189	Gobo 6 shake slow to fast	6
190-255	Rot. gobo wheel cont. rotation slow to fast	

31	29	48	0-255	Open to Close	4B
		49		**Blade 4B Fine :**	
			0-255	Open to Close Fine	4B
32	30	50		**All Blade Rotation (45° To -45°) :**	
			0-255	All Blade Rotation	(45° To -45°)
		51		**All Blade Rotation Fine :**	
			0-255	All Blade Rotation Fine	
33	31	52		**Speed Of Blade Speed:**	
			0-255	Speed Max >Min	
34	32	53		**Blade macro:**	
			0-15	OFF	
			16-30	Macro1	1
			31-45	Macro2	2
			46-60	Macro3	3
			61-75	Macro4	4
			76-90	Macro5	5
			91-105	Macro6	6
			106-120	Macro7	7
			121-135	Macro8	8
			136-150	Macro9	9
			151-165	Macro10	10
			166-180	Macro11	11
			181-195	Macro12	12
			196-210	Macro13	13
			211-225	Macro14	14
			226-240	Macro15	15
			241-255	Macro16	16
				Lamp on/off, reset, internal programs	
				Gobo change normal	
				Color change to any position	
				Gobo change to any position	
				No function	
				No function	
				All motor reset	8
				Scan motor reset	8
				Color motor reset	8
				Gobo motor reset	8
				No function	
				Other motor reset	8
				Internal program 1 (secne1~8 of EEPROM)	1 (1~8)
				Internal program 2 (secne9~16 of EEPROM)	2(9~16)
				Internal program 3 (secne17~24 of EEPROM)	3(17~24)
				Internal program 4 (secne25~32 of EEPROM)	4(25~32)
				Internal program 5 (secne33~40 of EEPROM)	5(33~40)
				Internal program 6 (secne41~48 of EEPROM)	6(41~48)
				Internal program 7 (secne49~56 of EEPROM)	7(49~56)
				No function	